

DESIGN OF DUAL-INPUT TWO PHASE DC/DC CONVERTER WITH
MODIFIED PULSE WIDTH MODULATION (MPWM)

AFARULRAZI BIN ABU BAKAR

A thesis submitted in
fulfillment of the requirement for the award of the
Degree of Doctor of Philosophy in Electrical Engineering

Faculty of Electrical and Electronic Engineering
Universiti Tun Hussein Onn Malaysia

SEPTEMBER 2019

Specially dedicated to my beloved family



ACKNOWLEDGEMENT

I would like to take this opportunity to express my deepest gratitude to my project supervisor, Ts. Dr. Asmarashid Bin Ponniran, who has persistently and determinedly assisted me during the whole course of this research. It would have been very difficult to complete this project without the enthusiastic support, insight and advice given by him.

My utmost thanks also go to my family who has given me support throughout my academic years. Without them, I might not be the person I am today.

Finally, my special gratitude is extended to all members of the F1 research group who has been my guide and for giving support for my research. It is my greatest thanks and joy that I have met this research group. Thank you.



ABSTRACT

Recently, hybrid energy source/renewable energy has attracted interest as the next-generation energy system capable of solving the problems of global warming and energy exhaustion caused by increasing energy consumption. Energy sources such as wind turbines and photovoltaic (PV) systems are intermittent, unpredictable and unregulated. For such systems, the use of multiple-input converter (MIC) has the advantage of regulating and controlling multiple-input sources. With multiple Pulsating Voltage-Source Cells (PVSC) configurations, the proposed converter can deliver power to the load individually and simultaneously. Also, it has the capability of operating either in buck, boost or buck–boost mode of operation. In addition, by proposing the enhanced Modified PWM (MPWM) switching scheme, it is able to solve the issues of the overlapping unregulated input sources. Furthermore, with the proposed multiphase configuration, the input current stresses in the switching devices are reduced and it has the benefit of a reduction in conduction losses. In addition, Zero-Voltage Switching (ZVS) technique is also employed in the proposed converter to reduce the switching loss. The proposed converter circuit is simulated by using MATLAB/Simulink and PSpice software programs. The duty cycle employed to regulate output voltage is reached from Altera DE2-70 board through dSPACE DS1103 board using by Proportional-Integral (PI) controller. The dual-input converter circuit model specification with output power at 200 W, input voltages that range from 10 to 60 V, and operating with dual switching frequencies of 50 kHz and 100 kHz is simulated to validate the designed parameters. Design guidelines, simulation and experimental results are presented. The results show that the proposed two-phase DC/DC converter with ZVS technique achieves 94% efficiency for all ranges of loads compared with the multiphase hard-switching. The total power losses across the power switches are reduced by approximately 37% in the proposed

converter. Thus, the proposed converter circuit model offers advantages on input current stress and switching loss reductions. The proposed circuit configuration can be used in a standalone hybrid energy system under unregulated DC input voltages. However the major disadvantages of resonant circuit are increased peak current and voltage stress and not suitable for variable frequency operation.



ABSTRAK

Baru-baru ini, sumber tenaga hibrid/tenaga boleh diperbaharui telah menarik minat sebagai sistem tenaga generasi seterusnya, mampu menyelesaikan masalah pemanasan global dan kekurangan tenaga yang disebabkan oleh peningkatan penggunaan tenaga. Walau bagaimanapun, sumber tenaga seperti sistem turbin angin dan sistem fotovoltai (PV) adalah berselang, tidak menentu dan tidak terkawal. Bagi sistem sedemikian, penggunaan penukar pelbagai input (MIC) mempunyai kelebihan untuk mengawal dan menyelia sumber-sumber masukan yang banyak. Dengan pelbagai konfigurasi Sel-Sumber-Voltan (PVSC), penukar yang dicadangkan boleh menyampaikan kuasa untuk memuatkan secara individu dan secara bersamaan. Selain itu, ia mempunyai keupayaan untuk mengendalikan sama ada dalam mod operasi menaik, menurun atau menaik dan menurun. Di samping itu, dengan mencadangkan skim penukaran PWM yang diperbaharui (MPWM), ia dapat menyelesaikan isu-isu sumber input bertindan yang tidak terkawal. Selain itu, dengan konfigurasi berbilang fasa yang dicadangkan, tegasan arus input dalam peranti pensuisan dikurangkan dan ia mendapat manfaat untuk pengurangan kehilangan pengaliran. Di samping itu, teknik penukaran Zero-Voltage Switching (ZVS) juga digunakan dalam penukar yang dicadangkan untuk mengurangkan kehilangan pensuisan. Litar penukar yang dicadangkan telah disimulasikan dengan menggunakan program perisian MATLAB/Simulink dan PSpice. Kitaran tugas yang digunakan untuk mengawal voltan keluaran dicapai dari papan Altera DE2-70 melalui dSPACE DS1103 yang menggunakan pengawal Proportional-Integral (PI). Spesifikasi model litar penukar dua masukan dengan daya output pada 200 W, voltan masukan adalah dari 10 ~ 60 V, dan beroperasi pada dua frekuensi iaitu 50 kHz dan 100 kHz disimulasikan untuk mengesahkan parameter yang dirancang. Garis panduan reka bentuk, simulasi dan hasil percubaan dibentangkan dengan jelas. Keputusan menunjukkan bahawa cadangan litar penukar dua fasa DC/DC dengan teknik ZVS yang dicadangkan mencapai 94% kecekapan untuk semua julat beban. Jumlah kehilangan kuasa di seluruh suis kuasa dikurangkan oleh kira-kira 37% daripada penukar yang dicadangkan. Oleh itu, model

litar penukar yang dicadangkan memberikan kelebihan kepada tegasan arus input dan mengurangkan kehilangan kerugian kuasa. Walau bagaimanapun kelemahan utama litar resonans peningkatan tekanan puncak semasa dan voltan dan tidak sesuai untuk operasi frekuensi pembolehubah.



CONTENTS

TITLE	i
DECLARATION	ii
ACKNOWLEDGEMENT	iv
ABSTRACT	v
ABSTRAK	vii
TABLE OF CONTENTS	ix
LIST OF TABLES	xiii
LIST OF FIGURES	xiv
LIST OF SYMBOLS AND ABBREVIATIONS	xxi
LIST OF APPENDICES	xxvi
CHAPTER 1 INTRODUCTION	1
1.1 Introduction	1
1.2 Research background	1
1.3 Problem statements	4
1.3 Research objectives	6
1.5 Research scopes	6
1.6 Thesis outline	7
CHAPTER 2 LITERATURE REVIEWS	9
2.1 Introduction	9
2.2 Multiple-input DC/DC converter	10
2.3 Advantages and disadvantages of non-isolated DC/DC converter	14
2.4 Input source configuration of multiple-input	16

	DC/DC converter	
2.5	Principle of input current ripple optimisation in multiphase DC/DC boost converter	19
2.6	Leakage inductance in PWM converters	23
2.7	Soft-switching technique for multiphase DC/DC boost converter	24
2.8	PID controller	27
2.9	DSP-based FPGA controller	28
2.10	Gaps of study	30
2.11	Summary	30
CHAPTER 3	RESEARCH METHODOLOGY	32
3.1	Introduction	32
3.2	Proposed multiple-input with multiphase DC/DC converter.	34
3.2.1	Principle design of multiphase DC/DC converter	35
3.2.2	Principle design of current ripple stress reduction with multiphase converter	39
3.2.3	Principle of design for zero-voltage switching (ZVS)	40
3.2.4	Principle of design of the proposed PWM switching scheme	44
3.2.5	Steady-state analysis of dual-input two phase DC/DC converter	48
3.2.6	Design guide of resonant components ($L_{r1,2}$ and $C_{r1,2}$)	56
3.3	Design procedure of the proposed switching scheme	57
3.3.1	Implementation of digital switching technique using FPGA and DSP	59
3.3.2	Design and implementation of PWM switching scheme	62

3.3.3	PWM switching design using Quartus II	63
3.3.4	Closed-loop design using MATLAB/Simulink software	66
3.4	Circuit simulation using MATLAB/Simulink and PSpice software	67
3.4.1	Circuit simulation using PSpice software	67
3.4.2	Circuit simulation using MATLAB/Simulink software	67
3.5	Hardware experimental setup	68
3.6	Performance analysis	69
3.6.1	Conduction loss	70
3.6.2	Switching losses	70

CHAPTER 4 RESULTS AND DISCUSSIONS

4.1	Introduction	73
4.2	Proposed switching scheme realisation	74
4.2.1	Switching pattern design using FPGA	74
4.2.2	Blanking time consideration on switching signal for the designed converter	76
4.3	Dual-input realisation based on open-loop control strategy	78
4.4	Dual-input converter realisation	81
4.4.1	Simulation and experimental results for single-input source	82
4.4.2	Balanced inputs observation	84
4.4.3	Unbalanced inputs observation	90
4.5	Power losses analysis of multiphase converter	96
4.5.1	Switching loss analysis	101
4.5.2	Conduction loss analysis	108
4.6	Closed-loop system response using PI controller	111

4.6.1	Output voltage ripple	112
4.6.2	System overshoot and undershoot	113
4.6.3	Sensitivity response (Dynamic response)	118
4.6.4	System performance	119
4.7	System efficiency	120
CHAPTER 5	CONCLUSION AND RECOMMENDATIONS	122
5.1	Conclusion	122
5.2	Recommendations	125
	REFERENCES	126
	APPENDICES A-K	147-195
	LIST OF PUBLICATIONS	196
	VITAE	200



LIST OF TABLES

2.1	Isolated and non-isolated multiple-input DC/DC converters related to application	16
2.2	Comparison of previous research related to proposed research topic	26
2.3	Gap of study of the multiple-input DC/DC converter according to the several recent works	30
3.1	Logical form to generate PWM signal using VHDL	64
3.2	Equipment used during the experimental analysis	68
3.3	Some significant values of the semiconductor devices used in the prototype circuit	69
4.1	The simulation and experimental results with different inputs, outputs and modes of operation	81
4.2	Experimental parameter setting	96
4.3	Calculated switching losses	107
4.4	Calculated conduction losses for single-phase and multiphase DC/DC converters	111
4.5	Summarised experimental results with three different parameters (K_P and K_I)	119

LIST OF FIGURES

2.1	DC input sources with: (a) individual DC/DC converters and (b) a single DC/DC converter	10
2.2	Non-isolated multiple-input DC/DC converter with single inductor [38]	11
2.3	Double-input DC/DC converter with one passive lossless soft-switching cell [47]	11
2.4	Proposed multiple-input DC/DC converter in [94]	12
2.5	A multiple-input boost converter for low-power energy harvesting [46]	13
2.6	Multiple-input DC/DC converter topology for hybrid energy system [33]	13
2.7	Equivalent circuit of the full-bridge configuration [95]	14
2.8	Typical derived MICs generated by series-connection of: (a) two buck PVSCs, (b) one buck PVSC and one full-bridge PVSC, (c) boost-and-Cuk PVSC (d) buck-and-Zeta PVSC and (e) buck PVSC [108]	16
2.9	Circuit configuration of: (a) buck PVSC and (b) multiple buck PVSCs with series connection	18
2.10	Switching technique for PVSC configurations: (a) intermediate synchronisation, (b) rising edge synchronisation, (c) falling edge synchronisation and (d) proposed switching signals	19
2.11	Normalised RMS input current ripples versus duty cycle with different phases [117]	20
2.12	Current ripples for interleaved switches with: (a) non-coupled inductor and (b) coupled inductor	21

2.13	Circuit configuration for (a) conventional single-phase DC/DC boost converter, (b) two-phase DC/DC boost converter and (c) multiphase DC/DC converter with N number of phase	22
2.14	Soft-switching techniques for (a) zero-voltage switching (ZVS) and (b) zero-current switching (ZCS)	24
2.15	Data rate versus arithmetic operation per sample for FPGA and DSP [164]	29
3.1	Block diagram of the proposed method	32
3.2	Flow chart of research methodology	33
3.3	Proposed dual-input multiphase converter circuit configuration	34
3.4	Two-phase DC/DC boost converter	36
3.5	Boost converter waveforms: (a) inductor voltage (b) inductor current (c) diode current (d) capacitor current	36
3.6	The variation of inductor current I_L versus duty cycle ($L=220 \mu\text{H}$)	39
3.7	PWM switching signal for two-phase DC/DC boost converter with: (a) non-interleaving and (b) interleaving	40
3.8	Normalised frequency versus voltage gain; $n=1$ and $h \leq 0$	42
3.9	Normalised frequency versus quality factor; $n=1$ and $h \leq 0$	42
3.10	Proposed PWM switching signals for S_1 , S_2 , S_3 and S_4	44
3.11	The output voltage of the proposed dual-input DC/DC converter	47
3.12	Waveform concerning the operation state of the proposed converter	49
3.13	Equivalent circuit scheme for the proposed converter with different state	50
3.14	PWM control of a multi-input interleaved DC/DC converter and the associated waveform for digital	58

	implementation	
3.15	Associated technique using digital implementation for switch: (a) S_1 (b) S_2 and (c) S_3 and S_4	59
3.16	Proposed flowchart to produce the gating signals of dual input DC/DC converter	60
3.17	Block diagram of the proposed design	62
3.18	Block diagram file (*.bdf) for PWM switching signal generation for S_1 , S_2 , S_3 and S_4	65
3.19	MATLAB/Simulink program for dSPACE DS1103 platform using PI controller	66
3.20	Overlapped current (x50) and voltage at MOSFET (off)	71
3.21	Overlapped current (x200) and voltage at MOSFET (on)	71
4.1	Experimental setup of the proposed converter	73
4.2	Simulation results for PWM switching for duty cycle $S_1=0.5$, $S_2=0.25$ and S_3 and $S_4=0.5$	74
4.3	Measured PWM switching signals for S_1 , S_2 , S_3 and S_4 with 0.5 duty cycle; voltage=20 V/div; time=10 μ s/div	75
4.4	Measured PWM switching signals for S_1 , S_2 , S_3 and S_4 with particular duty cycle	75
4.5	Experimental results of PWM switching signals for S_1 , S_2 , S_3 and S_4 at 0.5 duty cycle starved of blanking time	76
4.6	Experimental results of PWM signals for $S_1, S_2=0.3$ and $S_3, S_4=0.5$ duty cycle with appropriate adjusted blanking time	77
4.7	Experimental results of switching signals for dual-input (S_1 and S_2) and multiphase (S_3 and S_4) with blanking time	77
4.8	Operating modes for dual-input converter (buck) with different states for: (a) t_0-t_1 , (b) t_1-t_2 and (c) t_2-t_3	78
4.9	Measured voltage across V_L (Ch 2); gate pulses for S_1 (Ch 3) and S_2 (Ch 4) with duty cycles 0.5 and 0.3, respectively	79

4.10	Operating modes for dual-input converter (boost) with different states for: (a) t_0-t_1 , (b) t_1-t_2 and (c) t_2-t_3	79
4.11	Measured voltage across V_L (Ch 2); gate pulses for S_1 (Ch 3) and S_2 (Ch 4) with duty cycles 0.6 and 0.5, respectively	80
4.12	Simulation and experimental results for single input, $V_1= 16$ Volts and $V_2= 0$ Volt with measured output voltage $V_{out}=10$ Volts (buck mode)	82
4.13	Simulation and experimental results for single input, $V_1= 16$ Volts, $V_2= 0$ Volt and $V_{out}= 10$ Volts with inductor currents I_{L1} , I_{L2} and I_L	83
4.14	Simulation and experimental results for single input, $V_1= 16$ Volts and $V_2 = 0$ Volt with measured output voltage $V_{out}= 26$ Volts (boost mode)	83
4.15	Simulation and experimental results for single input, $V_1= 16$ Volts, $V_2= 0$ Volt and $V_{out}= 26$ Volts with inductor currents I_{L1} , I_{L2} and I_L	84
4.16	Simulation and experimental results for dual-inputs, $V_1= 12$ Volts and $V_2= 12$ Volts with measured output voltage $V_{out}= 16$ Volts (buck mode)	85
4.17	Simulation and experimental results for dual-inputs, $V_1= 12$ Volts, $V_2= 12$ Volts and $V_{out}= 16$ Volts with inductor currents I_{L1} , I_{L2} and I_L	86
4.18	Simulation and experimental results for dual-inputs, $V_1= 12$ Volts and $V_2= 12$ Volts with measured output voltage $V_{out}= 34$ Volts (boost mode)	86
4.19	Simulation and experimental results for dual-inputs, $V_1= 12$ Volts, $V_2= 12$ Volts and $V_{out}= 34$ Volts with inductor currents I_{L1} , I_{L2} and I_L	87
4.20	Simulation and experimental results for dual-inputs, $V_1= 16$ Volts and $V_2= 16$ Volts with measured output voltage $V_{out}= 26$ Volts (buck mode)	88
4.21	Simulation and experimental results for dual-inputs, $V_1= 16$ Volts, $V_2= 16$ Volts and $V_{out}= 26$ Volts with inductor currents I_{L1} , I_{L2} and I_L	88

4.22	Simulation and experimental results for dual-inputs, $V_1=16$ Volts and $V_2=16$ Volts with measured output voltage $V_{out}=36$ Volts (boost mode)	89
4.23	Simulation and experimental results for dual-input, $V_1=16$ Volts, $V_2=16$ Volts and $V_{out}=36$ Volts with inductor currents I_{L1} , I_{L2} and I_L	89
4.24	Simulation and experimental results for dual-inputs, $V_1=15$ Volts and $V_2=17$ Volts with measured output voltage $V_{out}=12$ Volts (buck mode)	90
4.25	Simulation and experimental results for single input, $V_1=15$ Volts, $V_2=17$ Volts and $V_{out}=12$ Volts with inductor currents I_{L1} , I_{L2} and I_L	91
4.26	Simulation and experimental results for dual-inputs, $V_1=15$ Volts and $V_2=17$ Volts with measured output voltage $V_{out}=38$ Volts (boost mode)	92
4.27	Simulation and experimental results for single input, $V_1=15$ Volts, $V_2=17$ Volts and $V_{out}=38$ Volts with inductor currents I_{L1} , I_{L2} and I_L	92
4.28	Simulation and experimental results for dual-inputs, $V_1=10$ Volts and $V_2=15$ Volts with measured output voltage $V_{out}=15$ Volts (buck mode)	93
4.29	Simulation and experimental results for single input, $V_1=10$ Volts, $V_2=15$ Volts and $V_{out}=15$ Volts with inductor currents I_{L1} , I_{L2} and I_L	93
4.30	Simulation and experimental results for dual-inputs, $V_1=10$ Volts and $V_2=15$ Volts with measured output voltage $V_{out}=35$ Volts (boost mode)	94
4.31	Simulation and experimental results for single input, $V_1=10$ Volts, $V_2=15$ Volts and $V_{out}=35$ Volts with inductor currents I_{L1} , I_{L2} and I_L	95
4.32	Circuit configuration for experimental setup, (a) conventional DC/DC boost converter, (b) multiphase DC/DC boost converter and (c) dual-input DC/DC converter with ZVS	97
4.33	Experimental results for drain-source voltage (V_{ds}) and drain-source current (I_{ds}) for: (a) circuit 1, (b) circuit 2,	98

	and (c) circuit 3	
4.34	Experimental results for drain-source voltage (V_{ds}), drain-source current (I_{ds}) and power across the switches for: (a) circuit 1, (b) circuit 2, and (c) circuit 3	100
4.35	Experimental results for switching losses during turn-on for: (a) circuit 1, (b) circuit 2, and (c) circuit 3	102
4.36	Experimental results for switching losses during turn-off for: (a) single-phase converter, (b) multiphase DC/DC converter and (c) multiphase converter with ZVS	104
4.37	Measured drain-source voltage and current for turn-on for 200 Watts: (a) multiphase converter and (b) multiphase converter with ZVS	105
4.38	Measured drain-source voltage and current for turn-off for 200 Watts: (a) multiphase converter and (b) multiphase converter with ZVS	106
4.39	Switching losses across the switches	107
4.40	Measured drain-voltage voltage and current for: (a) single-phase DC/DC converter, (b) multiphase DC/DC converter and (c) multiphase converter with ZVS at 50 Watts of output power	109
4.41	Measured drain-voltage voltage and current for: (a) single-phase DC/DC converter, (b) multiphase DC/DC converter and (c) multiphase converter with ZVS at 200 Watts of output power	110
4.42	Conduction losses versus output power	111
4.43	Measured output voltage ripple with different parameter setting	113
4.44	The experimental results for output voltage's sudden change from 20 Volts to 30 Volts with: (a) $K_p=4$, $K_f=0.0001$ (b) $K_p=2$, $K_f=0.0001$ and (c) $K_p=2$, $K_f=0.00001$	114
4.45	The experimental results for output voltage's sudden change from 30 Volts to 20 Volts with: (a) $K_p=4$, $K_f=0.0001$ (b) $K_p=2$, $K_f=0.0001$ and (c) $K_p=2$, $K_f=0.00001$	115

$K_I=0.00001$

- | | | |
|------|---|-----|
| 4.46 | The experimental results for output voltage's sudden change from 30 Volts to 38 Volts with: (a) $K_P=4$, $K_I=0.0001$ (b) $K_P=2$, $K_I=0.0001$ and (c) $K_P=2$, $K_I=0.00001$ | 116 |
| 4.47 | The experimental results for output voltage's sudden change from 38 Volts to 30 Volts with: (a) $K_P=4$, $K_I=0.0001$ (b) $K_P=2$, $K_I=0.0001$ and (c) $K_P=2$, $K_I=0.00001$ | 117 |
| 4.48 | Dynamic response of the proposed system using PI voltage control: (a) $K_P=4$; $K_I=0.0001$ (b) $K_P=2$; $K_I=0.0001$ and (c) $K_P=2$; $K_I=0.00001$ | 118 |
| 4.49 | Converter efficiency | 120 |
| 4.50 | Total power losses in semiconductor devices | 121 |



PTTA UTHM

PERPUSTAKAAN TUNKU TUN AMINAH

LIST OF SYMBOLS AND ABBREVIATIONS

A	-	Normalised switching frequency
ADC	-	Analog-to-digital converter
AC	-	Alternating Current
C	-	Capacitor
CCM	-	Continues Conduction Mode
C_{r1}	-	Resonant capacitor 1
C_{r2}	-	Resonant capacitor 2
CCTV	-	Closed-Circuit Television
D	-	Duty cycle
DPLL	-	Digital phase-locked loop
DC	-	Direct Current
D_{min}	-	Minimum duty cycle
D_1	-	Diode 1
D_2	-	Diode 2
DSP	-	Digital Signal Processing
DCM	-	Discontinuous Current Mode
DSC	-	Digital Signal Controller
EMI	-	Electromagnetic Interference
FPGA	-	Field Programmable Gate Arrays
f_o	-	Resonant frequency
f	-	Frequency

f_s	-	Switching frequency
f_{min}	-	Maximum frequency
h	-	Normalised initial resonant
HEV	-	Hybrid Electric Vehicles
Hz	-	Hertz
I_{max}	-	Maximum current
I_{min}	-	Minimum current
I_{ds}	-	Drain-source current
$I_{ds(on)}$	-	Drain-source current (on)
$I_{ds(off)}$	-	Drain-source current (off)
$I_{L(average)}$	-	Average inductor current
i_s	-	Current through switch
i_c	-	Current through capacitor
i_D	-	Current through diode
I_{SM}	-	Peak switch current
I_{omax}	-	Maximum output current
I_L	-	Inductor current
I_{L1}	-	Inductor current through L_1
I_{L2}	-	Inductor current through L_2
K_P	-	Proportional gain
K_I	-	Integral gain
L_{r1}	-	Resonant inductor 1
L_{r2}	-	Resonant inductor 2
L_{max}	-	Maximum inductor
L_{min}	-	Minimum inductor
L	-	Inductor

L_1	-	Inductor 1
L_2	-	Inductor 2
M	-	Input/output gain
MIC	-	Multiple-Input Converters
MISO	-	Multiple-Input Single-Output
MIMO	-	Multiple-Input Multiple-Output
MOSFET	-	Metal–Oxide–Semiconductor Field-Effect Transistor
MPWM	-	Modified Pulse Width Modulation
η	-	Efficiency
P	-	Power
PID	-	Proportional Integral Derivative
PV	-	Photovoltaic
PCWI	-	Pumping Capacitor Wire Inductance
PCCM	-	Pseudo-Continuous Conduction Mode
PCSC	-	Pulsating Current-Source Cell
PVSC	-	Pulsating Voltage-Source Cell
PWM	-	Pulse-Width Modulation
PFC	-	Power Factor Correction
P_T	-	Total power losses (watt)
P_{cond}	-	Conduction losses (watt)
P_{sw}	-	Switching losses (watt)
$P_{L(cu)}$	-	Copper loss (watt)
$P_{cond(switch)}$	-	Switch conduction losses (watt)
$P_{cond(diode)}$	-	Diode conduction losses (watt)
P_{Lon}	-	Switch turn-on power loss (watt)
P_{Loff}	-	Switch turn-off power loss (watt)

P_{in}	-	Input Power (watt)
P_{out}	-	Output Power (watt)
Q	-	Quality factor
Q_{min}	-	Maximum quality factor
Q_{max}	-	Minimum quality factor
r	-	Ripple factor
R	-	Resistor
R_{Lmin}	-	Maximum load resistance
R_{Lmax}	-	Minimum load resistance
RMS	-	Root-mean-square
RTI	-	Real-Time Interface
$R_{ds(on)}$	-	Drain-source on-state resistance
S	-	Power switch
SMPS	-	Switch-Mode Power Supply
S_1	-	Power switch 1
S_2	-	Power switch 2
T	-	Switching period
T_{off}	-	Switch off time
T_{on}	-	Switch on time
t_f	-	Fall time
t_r	-	Rise time
V_{in}	-	Input line voltage
V_s	-	Supply voltage
V_o	-	Output voltage
V_1	-	Input voltage source 1
V_2	-	Input voltage source 2

V_{ds}	-	Drain-source voltage
V_{ds1}	-	Drain-source voltage (switch 1)
V_{ds2}	-	Drain-source voltage (switch 2)
V_{gs}	-	Gate-source voltage
V_{gs1}	-	Gate-source voltage (switch 1)
V_{gs2}	-	Gate-source voltage (switch 2)
V_L	-	Inductor voltage
V_{L1}	-	Voltage across inductor 1
V_{L2}	-	Voltage across inductor 2
V_{out}	-	Output load voltage
V_{max}	-	Maximum voltage
V_{min}	-	Minimum voltage
V_{ref}	-	Reference voltage
V_F	-	Forward voltage drop
V_x	-	Voltage across diode
ZCS	-	Zero-Current Switching
ZVT	-	Zero- Voltage Transition
ZCT	-	Zero-Current Transition
ZVS	-	Zero-Voltage Switching
ΔQ	-	Ripple factor

REFERENCES

1. Y. Chen, Y. Liu, and F. Wu, "Multi-Input DC / DC Converter with Ripple-Free Input Currents," in *Power Electronics Specialists Conference*, 2002, pp. 796–802.
2. Y. Chen, Y. Liu, F. Wu, Yaow-Ming Chen, Yuan-Chuan Liu, and Feng-Yu Wu, "Multi-input DC/DC Converter Based on the Multiwinding Transformer for Renewable Energy Applications," *IEEE Transactions on Industry Applications*, vol. 38, no. 4, pp. 1096–1104, 2002.
3. M. Suetomi, H. Matsuo, R. Nakashima, R. Hamaguchi, Y. Isizuka, and W. Lin, "A Novel Multi-Input DC-DC Converter with High Power Efficiency," in *Telecommunications Energy Conference (INTELEC)*, 2011, pp. 1–5.
4. Y. Liu and Y. Chen, "A Systematic Approach to Synthesizing Multi-Input DC–DC Converters," *IEEE Transactions On Power Electronics*, vol. 24, no. 1, pp. 116–127, 2009.
5. S. Danyali, S. H. Hosseini, and G. B. Gharehpetian, "New Extendable Single-Stage Multi-Input DC – DC/AC Boost Converter," *IEEE Transactions On Power Electronics*, vol. 29, no. 2, pp. 775–788, 2014.
6. "Low Voltage | Definition of Low Voltage by Merriam-Webster." [Online]. Available: [https://www.merriam-webster.com/dictionary/low voltage](https://www.merriam-webster.com/dictionary/low%20voltage). [Accessed: 23-Jul-2017].
7. "Solar & DC Air Conditioners | 48v DC Solar & Telecom Air Conditioner Heat Pump | Off-Grid Air Conditioning." [Online]. Available: <http://www.hotspotenergy.com/DC-air-conditioner/>. [Accessed: 31-Jul-2017].
8. "DC-Powered Solar Refrigerators | Green Energy Innovations." [Online]. Available: <http://www.geinnovations.net/solarrefrigerator.html>. [Accessed:

31-Jul-2017].

9. J. B. R. Cabral, T. Lemes da Silva, S. V. G. Oliveira, and Y. R. de Novaes, "A New High Gain Non-Isolated DC-DC Boost Converter for Photovoltaic Application," in *2013 Brazilian Power Electronics Conference*, 2013, pp. 569–574.
10. M. M. Amin and O. A. Mohammed, "A Novel Grid-Connected Multi-Input Boost Converter for HEVs: Design and Implementation," in *IEEE International Electric Vehicle Conference (IEVC)*, 2012, pp. 1–7.
11. C. Zheng, W. Yu, J. J. Lai, and H. Ma, "Single-Switch Three-Level Boost Converter for PWM Dimming LED Lighting," in *Energy Conversion Congress and Exposition (ECCE)*, 2011, pp. 2589–2596.
12. S.H.Hosseini, S. K. Haghghian, S. Danyali, and H. Aghazadeh, "Multi-Input DC Boost Converter Supplied by a Hybrid PV / Wind Turbine Power Systems for Street Lighting Application Connected to the Grid," in *Universities Power Engineering Conference (UPEC)*, 2012, pp. 1–6.
13. M. H. Rashid, *Power Electronics Handbook*, 3rd ed. Elsevier, 2011.
14. K. H. Jasmine and C. R. Raj, "A High Gain Boost Converter with Input Current Ripple Reduction," in *2014 International Conference on Circuit, Power and Computing Technologies [ICCPCT]*, 2014, pp. 455–460.
15. M. Muhammad, M. Armstrong, and M. Elgendy, "A Non-isolated Interleaved Boost Converter for High Voltage Gain Applications.," *IEEE Journal of Emerging and Selected Topics in Power Electronics*, vol. 6777, no. c, pp. 1–1, 2015.
16. K. Lee, B. Park, R. Kim, and D. Hyun, "Nonisolated ZVT Two-Inductor Boost Converter With a Single Resonant Inductor for High Step-Up Applications," *IEEE Transactions On Power Electronics*, vol. 27, no. 4, pp. 1966–1973, 2012.
17. Taufik, P. Luther, and M. Anwari, "Digitally Controlled ZVS Quasi-Resonant Boost Converter with M-type Switch," in *International Conference on*

Intelligent and Advanced Systems, 2007, pp. 823–828.

18. M. K. Kazimierczuk, “Design-Oriented Analysis of Boost Zero-Voltage-Switching Resonant DC / DC Converter,” *IEEE Transactions on Power Electronics*, vol. 3, no. 2, pp. 126–136, 1988.
19. S.-H. Park, S.-R. Park, J.-S. Yu, Y.-C. Jung, J. Yu, and C.-Y. Won, “Analysis and Design of a Soft-Switching Boost Converter With an HI-Bridge Auxiliary Resonant Circuit,” *IEEE Transactions On Power Electronics*, vol. 25, no. 8, pp. 2142–2149, 2010.
20. Y. Hsieh, T. Hsueh, and H. Yen, “An Interleaved Boost Converter With Zero-Voltage Transition,” *IEEE Transactions On Power Electronics*, vol. 24, no. 4, pp. 973–978, 2009.
21. R. C. N. Pilawa-podgurski, A. D. Sagneri, J. M. Rivas, D. I. Anderson, and D. J. Perreault, “Very-High-Frequency Resonant Boost Converters,” *IEEE Transactions on Power Electronics*, vol. 24, no. 6, pp. 1654–1665, 2009.
22. C. Da Cunha Duarte and I. Barbi, “A New Family of ZVS-PWM Active-Clamping DC-to-DC Boost Converters: Analysis, Design, and Experimentation,” *IEEE Transactions on Power Electronics*, vol. 12, no. 5, pp. 824–831, 1997.
23. M. Rezvanyvardom, E. Adib, and H. Farzanehfard, “New Interleaved Zero-Current Switching Pulse-Width Modulation Boost Converter with One Auxiliary Switch,” *IET Power Electronics*, vol. 4, no. 9, p. 979, 2011.
24. M. Mohammadi, H. Farzanehfard, E. Adib, and M. Rezvanyvardom, “Analysis, Design and Implementation of Zero-Current Transition Interleaved Boost Converter,” *IET Power Electronics*, vol. 5, no. 9, pp. 1804–1812, Nov. 2012.
25. I. Aksoy, H. Bodur, and A. F. Bakan, “A New ZVT-ZCT-PWM DC – DC Converter,” *IEEE Transactions On Power Electronics*, vol. 25, no. 8, pp. 2093–2105, 2010.
26. W. Li and X. He, “ZVT Interleaved Boost Converters for High-Efficiency ,

- High Step-Up DC – DC Conversion,” *IET Electr. Power Appl.*, no. 2, pp. 284–290, 2007.
27. W. Li, X. Xiang, C. Li, W. Li, and X. He, “Interleaved High Step-Up ZVT Converter With Built-In Transformer Voltage Doubler Cell for Distributed PV Generation System,” *IEEE Transactions On Power Electronics*, vol. 28, no. 1, pp. 300–313, 2013.
 28. R. Gurunathan and A. K. S. Bhat, “A Zero-Voltage Transition Boost Converter using a Zero-Voltage Switching Auxiliary Circuit,” *IEEE Transactions on Power Electronics*, vol. 17, no. 5, pp. 658–668, 2002.
 29. H. Do, “Interleaved Boost Converter with a Single Magnetic Component,” *IET Power Electronics*, vol. 4, no. August 2010, pp. 842–849, 2011.
 30. H. Bodur, S. Cetin, and G. Yanik, “A New Zero-Voltage Transition Pulse Width Modulated Boost Converter,” *IET Power Electronics*, vol. 4, no. 7, p. 827, 2011.
 31. C. Y. Lee, G. Hua, C. Leu, Y. Jiang, and F. C. Y. Lee, “Novel Zero-Voltage-Transition PWM Converters,” *IEEE Transactions On Power Electronics*, vol. 9, no. 2, pp. 213–219, 1994.
 32. M. R. Islam, N. A. Rahim, K. H. Solangi, and E. Tower, “Renewable Energy Research in Malaysia,” in *Engineering e-Transaction*, 2010, vol. 4, no. 2, pp. 69–72.
 33. S. Jain and L. Kumar, “Multiple-Input DC/DC Converter Topology for Hybrid Energy System,” *IET Power Electronics*, vol. 6, no. 8, pp. 1483–1501, Sep. 2013.
 34. A. Di Napoli, F. Crescimbeni, L. Solero, F. Caricchi, and F. G. Capponi, “Multiple-Input DC-DC Power Converter for Power-Flow Management in Hybrid Vehicles,” in *Conference Record of the 2002 IEEE Industry Applications Conference. 37th IAS Annual Meeting (Cat. No.02CH37344)*, 2002, vol. 3, pp. 1578–1585.
 35. T. Taufik and T. Wong, “Multiple-Input Single-Output Converter for

- Renewable Energy Sources,” in *IEEE Symposium on Industrial Electronics and Applications (ISIEA2012)*, 2012, pp. 130–135.
36. A. Kwasinski and P. T. Krein, “Multiple-Input Dc-Dc Converters to Enhance Local Availability in Grids using Distributed Generation Resources,” in *Conference Proceedings - IEEE Applied Power Electronics Conference and Exposition - APEC*, 2007, pp. 1657–1663.
 37. D. Patil and V. Agarwal, “Multi-Input DC-AC Converter for Renewable Energy Applications,” in *ECCE Asia Downunder (ECCE Asia)*, 2013, no. c, pp. 429–435.
 38. A. Khaligh, J. Cao, and Y. Lee, “A Multiple-Input DC–DC Converter Topology,” *IEEE Transactions On Power Electronics*, vol. 24, no. 3, pp. 862–868, 2009.
 39. S. H. Hosseini, S. Danyali, F. Nejabatkhah, and S. A. K. H. M. Niapoor, “Multi-Input DC Boost Converter for Grid Connected Hybrid PV / FC / Battery Power System,” in *IEEE Electric Power and Energy Conference (EPEC)*, 2010, pp. 1–6.
 40. M. Jafari, G. Hunter, and J. G. Zhu, “A New Topology of Multi-Input Multi-Output Buck-Boost DC-DC Converter for Microgrid Applications,” in *IEEE International Conference on Power and Energy (PECon)*, 2012, no. December, pp. 2–5.
 41. L. Schuch, C. Rech, H. L. Hey, H. A. Gründling, H. Pinheiro, and J. R. Pinheiro, “Analysis and Design of a New High-Efficiency Bidirectional Integrated ZVT PWM Converter for DC-Bus and Battery-Bank Interface,” *IEEE Transactions On Industry Applications*, vol. 42, no. 5, pp. 1321–1332, 2006.
 42. S. Poshtkouhi and O. Trescases, “Multi-input Single-inductor DC-DC Converter for MPPT in Parallel-Connected Photovoltaic Applications,” in *Applied Power Electronics Conference and Exposition (APEC)*, 2011, vol. 4, pp. 41–47.
 43. C.-L. Shen, C. Tsai, Y. Wu, and C. Chen, “A Modified-Forward Multi-input

- Power Converter for Solar Energy and Wind Power Generation,” in *PEDS2009*, 2009, pp. 631–636.
44. S. Dusmez *et al.*, “A New Multiinput Three-Level DC/DC Converter,” *IEEE Transactions on Power Electronics*, vol. 31, no. 2, pp. 1230–1240, 2016.
 45. B. G. Dobbs and P. L. Chapman, “A Multiple-Input DC-DC Converter Topology,” *IEEE Power Electronics Letters*, vol. 1, no. 1, pp. 6–9, 2003.
 46. C. Shi, B. Miller, K. Mayaram, and T. Fiez, “A Multiple-Input Boost Converter for Low-Power Energy Harvesting,” *IEEE Transactions on Circuits and Systems II: Express Briefs*, vol. 58, no. 12, pp. 827–831, 2011.
 47. Y. Chen, Y. Liu, and S. Lin, “Double-Input PWM DC/DC Converter for High/Low Voltage Sources,” in *The 25th International Telecommunications Energy Conference, 2003. INTELEC '03.*, 2003, pp. 27–32.
 48. D. Diaz, D. Meneses, J. A. Oliver, O. Garcia, P. Alou, and J. A. Cobos, “Dynamic Analysis of a Boost Converter with Ripple Cancellation Network by Model-Reduction Techniques,” *IEEE Transactions on Power Electronics*, vol. 24, no. 12, pp. 2769–2775, 2009.
 49. A. H. El Khateb, N. A. Rahim, J. Selvaraj, and B. W. Williams, “DC-to-DC Converter with Low Input Current Ripple for Maximum Photovoltaic Power Extraction,” *IEEE Transactions on Industrial Electronics*, vol. 62, no. 4, pp. 2246–2256, 2015.
 50. Y. Gu and D. Zhang, “Interleaved Boost Converter with Ripple Cancellation Network,” *IEEE Transactions on Power Electronics*, vol. 28, no. 8, pp. 3860–3869, 2013.
 51. B. R. Lin and C. L. Huang, “Interleaved ZVS Converter with Ripple-Current Cancellation,” *IEEE Transactions on Industrial Electronics*, vol. 55, no. 4, pp. 1576–1585, 2008.
 52. C. S. Leu, P. Y. Huang, and M. H. Li, “A Novel Dual-Inductor Boost Converter with Ripple Cancellation for High-Voltage-Gain Applications,” *IEEE Transactions on Industrial Electronics*, vol. 58, no. 4, pp. 1268–1273,

2011.

53. K. Yao, X. Hu, Q. Li, and M. Yin, "A Novel Control to Achieve Optimal Reduction of the E-Cap's Ripple Current for Discontinuous-Conduction Mode Boost PFC Converter," *IEEE Transactions on Power Electronics*, vol. 31, no. 6, pp. 4331–4342, 2016.
54. A. Chub, L. Liivik, J. Zakis, and D. Vinnikov, "Improved Switched-Inductor Quasi-Switched-Boost Inverter with Low Input Current Ripple," in *56th International Scientific on Power and Electrical Engineering of Riga Technical University (RTUCON)*, 2015.
55. A. R. Naderi and K. Abbaszadeh, "High Gain Boost Converter for Input Current Ripple Applying an Optimized Switching Strategy to a Cancellation," in *8th Power Electronics, Drive Systems & Technologies Conference (PEDSTC 2017)*, 2017, pp. 7–12.
56. X. Hu, B. Gao, Q. Wang, L. Li, and H. Chen, "A Zero Ripple Input Current Boost Converter for High Gain Applications," in *IEEE Journal of Emerging and Selected Topics in Power Electronics*, 2017, vol. PP, no. 99.
57. R. Hosoki, S. Kinjo, and H. Koizumi, "Ripple Free Operation of Two-Stage Boost Type DC-DC Converter," in *IECON 2015 - 41st Annual Conference of the IEEE Industrial Electronics Society*, 2015, pp. 577–582.
58. G. Marsala and A. Ragusa, "Free Ripple Input Current High Boost Converter with Coupled Inductors," in *Electric Utility Deregulation and Restructuring and Power Technologies*, 2015, pp. 2195–2200.
59. M. Veerachary and J. Prakash, "Low Source Current Ripple Soft-Switching Boost Converter," in *Biennial International Conference on Power and Energy Systems: Towards Sustainable Energy (PESTSE)*, 2016.
60. D. B. W. Abeywardana, B. Hredzak, and V. G. Agelidis, "DC Side Ripple Current Reduction Method for Three-Phase Boost Inverter with Mismatched Output Capacitors," in *IEEE PES Innovative Smart Grid Technologies Conference Europe*, 2016, pp. 208–213.

61. S. Lee and H. Do, "Boost-Integrated Two-Switch Forward AC-DC LED Driver With High Power Factor and Ripple-Free Output Inductor Current," *IEEE Transactions On Industrial Electronics*, vol. 64, no. 7, pp. 5789–5796, 2017.
62. C.-F. Tang, K.-H. Chen, C.-L. Wey, Y.-H. Lin, J.-R. Lin, and T.-Y. Tsia, "Ultra-Low Voltage Ripple in DC-DC Boost Converter by the Pumping Capacitor and Wire Inductance Technique," in *IEEE Asian Solid-State Circuits Conference*, 2016, pp. 301–304.
63. Z. Chen and J. Xu, "High Boost Ratio DC-DC Converter with Ripple-Free Input Current," *Electronics Letters*, vol. 50, no. 5, pp. 353–354, 2014.
64. V. L. Tran, N. T. Tran, S. H. Yu, Y. Park, and W. Choi, "Design of a Nonisolated Fuel Cell Boost Charger for Lithium Polymer Batteries with a Low Output Ripple," *IEEE Transactions on Energy Conversion*, vol. 30, no. 2, pp. 605–614, 2015.
65. C. A. Soriano-Rangel, J. C. Rosas-Caro, and F. Mancilla-David, "An Optimized Switching Strategy for a Ripple-Canceling Boost Converter," *IEEE Transactions on Industrial Electronics*, vol. 62, no. 7, pp. 4226–4230, 2015.
66. M. A. Devi, K. Valarmathi, and R. Mahendran, "Ripple Current Reduction in Interleaved Boost Converter by using Advanced PWM Techniques," in *2014 IEEE International Conference on Advanced Communication Control and Computing Technologies (ICACCCT)*, 2014, no. 978, pp. 115–119.
67. M. Veerachary and M. N. V Bhavana, "Low Source Current-Ripple High Gain Boost Converter," in *9th International Conference on Industrial and Information Systems (ICIIS)*, 2014, pp. 1–6.
68. K. Yao, X. Hu, W. Hu, W. Tang, and J. Lyu, "A Novel Variable Duty Cycle Control to Achieve Optimal Reduction of the Electrolytic Capacitor Ripple Current for DCM Boost PFC Converter," in *Conference Proceedings - IEEE Applied Power Electronics Conference and Exposition - APEC*, 2015, pp. 485–491.
69. J. H. Lee, J. H. Kim, C. Y. Won, S. J. Jang, and Y. C. Jung, "Soft Switching

- Multi-Phase Boost Converter for Photovoltaic System,” in *2008 13th International Power Electronics and Motion Control Conference, EPE-PEMC 2008*, 2008, pp. 1924–1928.
70. G. Yao, A. Chen, and X. He, “Soft Switching Circuit for Interleaved Boost Converters,” *IEEE Transactions On Power Electronics*, vol. 22, no. 1, pp. 80–86, 2007.
 71. M. A. Al-Saffar, E. H. Ismail, and A. J. Sabzali, “Family of ZC-ZVS Converters with Wide Voltage Range for Renewable Energy Systems,” *Renewable Energy*, vol. 56, pp. 32–43, Aug. 2013.
 72. K. Deepa and M. V. Kumar, “ZVS Multi-output Push-pull QRC Using Analog Controller UC3825 for Low Power Applications,” *AASRI Procedia*, vol. 7, pp. 62–67, 2014.
 73. B. Lin and J. Chen, “Hybrid ZVS Converter with a Wide ZVS Range and a Low Circulating Current,” *Journal of Power Electronics*, vol. 15, no. 3, pp. 652–659, 2015.
 74. H. Jin, H. Kim, and D. Son, “A Boost-Input Self-Driven Active Clamp ZVS Converter,” in *International Conference on Electrical Machines and Systems (ICEMS)*, 2010, pp. 380–383.
 75. M. Baei and G. Moschopoulos, “A ZVS-PWM Full-Bridge Boost Converter for Applications Needing High Step-Up Voltage Ratio,” pp. 2213–2217, 2012.
 76. R. Wai, C. Lin, J. Liaw, and Y. Chang, “Newly Designed ZVS Multi-Input Converter,” *IEEE Transactions On Industrial Electronics*, vol. 58, no. 2, pp. 555–566, 2011.
 77. N. Guangqun and H. Xue, “Novel Full-bridge ZVS DC-DC Converter with an Clamp Diodes,” *Physics Procedia*, vol. 33, pp. 1964–1970, 2012.
 78. M. Baei, M. Narimani, and G. Moschopoulos, “A new ZVS-PWM Full-Bridge Boost Converter,” *Journal of Power Electronics*, vol. 14, no. 2, pp. 237–248, 2014.
 79. R. Gurunathan and A. K. S. Bhat, “ZVT Boost Converter Using a ZCS

- Auxiliary Circuit,” *IEEE Transactions On Aerospace And Electronic Systems*, vol. 37, no. 3, pp. 889–897, 2001.
80. C. C. Wu and C. M. Young, “ZVT-PWM AC-DC Boost Converter with ZCS Auxiliary Circuit,” *Electronics Letters*, vol. 38, no. 10, pp. 442–443, 2002.
 81. A. Mohammadpour, L. Parsa, M. H. Todorovic, R. Lai, and R. Datta, “Interleaved Multi-Phase ZCS Isolated DC-DC Converter for Sub-Sea Power Distribution,” in *IECON 2013*, 2013, pp. 924–929.
 82. C. A. Canesin and F. A. S. Goncalves, “Multi-Cell Variable Frequency Interleaved ZCS Boost Rectifier Digitally Controlled by FPGA,” in *IEEE ISIE*, 2006, pp. 1382–1387.
 83. V. Najmi, S. Ebrahimi, S. Sharifan, and H. Oraee, “A Novel ZVS-ZCS Boost Converter with an H-Bridge Auxiliary LCC Resonant Circuit,” in *IEEE International Conference on Power and Energy*, 2012, no. December, pp. 18–21.
 84. A. Di Napoli, F. Crescimbeni, S. Rodo, and L. Solero, “Multiple Input DC-DC Power Converter for Fuel-Cell Powered Hybrid Vehicles,” in *2002 IEEE 33rd Annual IEEE Power Electronics Specialists Conference. Proceedings (Cat. No.02CH37289)*, 2002, vol. 4, pp. 1685–1690.
 85. A. Di Napoli, F. Crescimbeni, F. G. Capponi, and L. Solero, “Control Strategy for Multiple Input DC-DC Power Converters Devoted to Hybrid Vehicle Propulsion Systems,” in *Industrial Electronics, 2002. ISIE 2002. Proceedings of the 2002 IEEE International Symposium on*, 2002, vol. 3, pp. 1036–1041.
 86. S. Kabir, M. S. Islam, M. Aminuzzaman, A. Ahmed, and M. R. H. Khan, “Renewable integrated Hybrid Power Management for Off Grid Base Transceiver Station (BTS): Microcontroller Based,” *2nd International Conference on Electrical Engineering and Information and Communication Technology, iCEEiCT 2015*, no. May, pp. 21–23, 2015.
 87. T. Erfanmanesh and M. Dehghani, “Performance Improvement in Grid-Connected Fuel Cell Power Plant: An LPV Robust Control Approach,” *International Journal of Electrical Power & Energy Systems*, vol. 67, pp. 306–

314, 2015.

88. K. Gummi and M. Ferdowsi, "Double-input DC-DC Power Electronic Converters for Electric-Drive Vehicles- Topology Exploration and Synthesis using a Single-Pole Triple-Throw Switch," *IEEE Transactions on Industrial Electronics*, vol. 57, no. 2, pp. 617–623, 2010.
89. L. Kumar and S. Jain, "A Novel Multiple Input DC-DC Converter for Electric Vehicular Applications," in *2012 IEEE Transportation Electrification Conference and Expo, ITEC 2012*, 2012, pp. 0–5.
90. R. Ahmadi and M. Ferdowsi, "Double-Input Converters Based on H-Bridge Cells: Derivation, Small-Signal Modeling, and Power Sharing Analysis," *IEEE Transactions on Circuits and Systems I: Regular Papers*, vol. 59, no. 4, pp. 875–888, 2012.
91. Y. M. Chen, Y. C. Liu, and S. H. Lin, "Double-Input PWM DC/DC Converter for High-/Low-Voltage Sources," *IEEE Transactions on Industrial Electronics*, vol. 53, no. 5, pp. 1538–1545, 2006.
92. H. Matsuo, W. Lin, F. Kurokawa, T. Shigemizu, and N. Watanabe, "Characteristics of the Multiple-Input DC–DC Converter," *IEEE Transactions On Industrial Electronics*, vol. 51, no. 3, pp. 625–631, 2004.
93. L. Solero, A. Lidozzi, and J. A. Pomilio, "Design of Multiple-Input Power Converter for Hybrid Vehicles," *IEEE Transactions On Power Electronics*, vol. 20, no. 5, pp. 1007–1016, 2005.
94. Z. Qian, O. Abdel-Rahman, and I. Batarseh, "An Integrated Four-Port DC/DC Converter for Renewable Energy Applications," *IEEE Transactions on Power Electronics*, vol. 25, no. 7, pp. 1877–1887, 2010.
95. F. Guo, L. Fu, X. Zhang, C. Yao, H. Li, and J. Wang, "A Family of Quasi-Switched-Capacitor Circuit-Based Dual-Input DC/DC Converters for Photovoltaic Systems Integrated with Battery Energy Storage," *IEEE Transactions on Power Electronics*, vol. 31, no. 12, pp. 8237–8246, 2016.
96. F. Pareschi, R. Rovatti, and G. Setti, "EMI Reduction via Spread Spectrum in

- DC/DC Converters: State of the Art, Optimization, and Tradeoffs,” *IEEE Access*, vol. 3, no. January 2016, pp. 2857–2874, 2015.
97. Q. Wang, J. Zhang, X. Ruan, and K. Jin, “Double-Input Flyback DC/DC Converter with Single Primary Winding,” in *2010 IEEE Energy Conversion Congress and Exposition, ECCE 2010 - Proceedings*, 2010, pp. 1938–1944.
 98. K. Varesi, S. H. Hosseini, M. Sabahi, E. Babaei, and N. Vosoughi, “Performance and Design Analysis of an Improved Non-Isolated Multiple Input Buck DC–DC Converter,” *IET Power Electronics*, vol. 10, no. 9, pp. 1034–1045, 2017.
 99. F. Akar, Y. Tavlasoglu, E. Ugur, B. Vural, and I. Aksoy, “A Bidirectional Nonisolated Multi-Input DC–DC Converter for Hybrid Energy Storage Systems in Electric Vehicles,” *IEEE Transactions on Vehicular Technology*, vol. PP, no. 99, p. 1, 2015.
 100. F. Liu, Z. Wang, Y. Mao, and X. Ruan, “Asymmetrical Half-Bridge Double-Input DC / DC Converters Adopting Pulsating Voltage Source Cells for Low Power Applications,” *IEEE Transactions On Power Electronics*, vol. 29, no. 9, pp. 4741–4751, 2014.
 101. S. Dusmez, X. Li, and B. Akin, “A New Multiinput Three-Level DC/DC Converter,” *IEEE Transactions on Power Electronics*, vol. 31, no. 2, pp. 1230–1240, 2016.
 102. T. K. Santhosh, K. Natarajan, and C. Govindaraju, “Synthesis and Implementation of Multi-Port DC/DC Converter for Hybrid Electric Vehicle,” *Journal of Power Electronics*, vol. 15, no. 5, pp. 1178–1189, 2015.
 103. S. Hou, J. Chen, T. Sun, and X. Bi, “Multi-input Step-Up Converters Based on the Switched-Diode-Capacitor Voltage Accumulator,” *IEEE Transactions on Power Electronics*, vol. 31, no. 1, pp. 381–393, 2016.
 104. H. Behjati and A. Davoudi, “Single-stage multi-port DC–DC converter topology,” *IET Power Electronics*, vol. 6, no. 2, pp. 392–403, Feb. 2012.
 105. O. C. Onar, O. H. A. Shirazi, and A. Khaligh, “Grid Interaction Operation of a

- Telecommunications Power System with a Novel Topology for Multiple-Input Buck-Boost Converter,” *IEEE Transactions on Power Delivery*, vol. 25, no. 4, pp. 2633–2645, 2010.
106. A. Hintz, U. R. Prasanna, and K. Rajashekara, “Novel Modular Multiple-Input Bidirectional DC- DC Power Converter (MIPC) for HEV / FCV Application,” *IEEE Transactions on Industrial Electronics*, vol. 0046, no. c, pp. 3163–3172, 2015.
 107. A. Kwasinski, “Identification of Feasible Topologies for Multiple-Input DC – DC Converters,” *IEEE Transactions On Power Electronics*, vol. 24, no. 3, pp. 856–861, 2009.
 108. Y. Li, X. Ruan, D. Yang, F. Liu, and C. K. Tse, “Synthesis of Multiple-Input DC / DC Converters,” *IEEE Transactions On Power Electronics*, vol. 25, no. 9, pp. 2372–2385, 2010.
 109. L. Kumar and S. Jain, “A Multiple Source DC/DC Converter Topology,” *International Journal of Electrical Power & Energy Systems*, vol. 51, pp. 278–291, 2013.
 110. F. Liu, Y. Mao, Z. Wang, and X. Ruan, “Asymmetrical Bridge Double-Input DC/DC Converters Adopting Pulsating Voltage Source Cells,” *IEEE Energy Conversion Congress and Exposition: Energy Conversion Innovation for a Clean Energy Future, ECCE 2011, Proceedings*, no. c, pp. 421–428, 2011.
 111. N. Agrawal, L. Kumar, and S. Ghosh, “Power Management in Double-Input DC / DC Converter,” in *1st IEEE International Conference on Power Electronics, Intelligent Control and Energy Systems*, 2016, pp. 1–6.
 112. B. C. Barry, J. G. Hayes, M. G. Egan, M. S. Rylko, J. W. Maslon, and K. J. Hartnett, “CCM and DCM Operation of the Integrated-Magnetic Interleaved Two-Phase Boost Converter,” *IEEE Transactions On Power Electronics*, vol. 30, no. 12, pp. 6551–6567, 2015.
 113. W. Li, Y. Zhao, J. Wu, and X. He, “Interleaved High Step-Up Converter with Winding-Cross-Coupled Inductors and Voltage Multiplier Cells,” *IEEE Transactions on Power Electronics*, vol. 27, no. 1, pp. 133–143, 2012.

114. Y.-T. Chen, T.-M. Li, and R.-H. Liang, "A Novel Soft-Switching Interleaved Coupled-Inductor Boost Converter with Only Single Auxiliary Circuit," *IEEE Transactions on Power Electronics*, vol. 33, no. 3, pp. 2267–2281, 2017.
115. S. Lee, S. Rhee, and G. Moon, "Coupled Inductor Incorporated Boost Half-Bridge Converter With Wide ZVS Operation Range," *IEEE Transactions On Industrial Electronics*, vol. 56, no. 7, pp. 2505–2512, 2009.
116. J. Xu, P. Yang, M. He, F. Zhang, and T. Yan, "High-Efficiency Two-Switch Tri-State Buck–Boost Power Factor Correction Converter with Fast Dynamic Response and Low-Inductor Current Ripple," *IET Power Electronics*, vol. 6, no. 8, pp. 1544–1554, Sep. 2013.
117. G. Choe, J. Kim, H. Kang, and B. Lee, "An Optimal Design Methodology of an Interleaved Boost Converter for Fuel Cell Applications," vol. 5, no. 2, 2010.
118. D. Jung, Y. Ji, S. Park, Y. Jung, and C. Won, "Interleaved Soft-Switching Boost Converter for Photovoltaic Power-Generation System," *IEEE Transactions On Power Electronics*, vol. 26, no. 4, pp. 1137–1145, 2011.
119. S. Y. Tseng, J. Z. Shiang, H. H. Chang, W. S. Jwo, and C. T. Hsieh, "A Novel Turn-on/off Snubber for Interleaved Boost Converters," *PESC Record - IEEE Annual Power Electronics Specialists Conference*, pp. 2341–2347, 2007.
120. P. W. Lee, Y. S. Lee, D. K. W. Cheng, and X. C. Liu, "Steady-State Analysis of an Interleaved Boost Converter with Coupled Inductors," *IEEE Transactions on Industrial Electronics*, vol. 47, no. 4, pp. 787–795, 2000.
121. J. S. A. Rahavi, T. Kanagapriya, and R. Seyezhai, "Design and Analysis of Interleaved Boost Converter for Renewable Energy Source," *International Conference on Computing, Electronics and Electrical Technologies (ICCEET), 2012 .*, pp. 447–451, 2012.
122. H.-B. Shin, J.-G. Park, S.-K. Chung, H.-W. Lee, and T. A. Lipo, "Generalised Steady-State Analysis of Multiphase Interleaved Boost Converter with Coupled Inductors," *IEE Proceedings - Electric Power Applications*, vol. 152, no. 3, pp. 1161–1170, 2005.

123. A. A. A. Bakar, W. M. M. Utomo, S. A. A. Zulkifli, E. Sulaiman, M. Z. Z. Ahmad, and M. Jenal, "DC-DC Interleaved Boost Converter using FPGA," in *IEEE Conference on Clean Energy and Technology*, 2013, pp. 97–100.
124. S. Pathy and N. Hari, "A Modified Module Integrated - Interleaved Boost Converter for Standalone Photovoltaic (PV) Application," vol. 5.
125. H. Liu and D. Zhang, "Two-Phase Interleaved Inverse-Coupled Inductor Boost Without Right Half-Plane Zeros," *IEEE Transactions on Power Electronics*, vol. 32, no. 3, pp. 1844–1859, 2017.
126. G. M. V. Gil, E. O. H. Catata, J. C. C. Ccarita, J. G. Cardoso, A. J. S. Filho, and J. L. Azcue-Puma, "Digital Controller Design for Interleaved Boost Converter in Photovoltaic System," in *2016 12th IEEE International Conference on Industry Applications (INDUSCON)*, 2016.
127. G. Valbuena and E. Mojica-Nava, "Digital Control for an Interleaved Boost Converter in a DC Microgrid," in *2016 IEEE Colombian Conference on Robotics and Automation (CCRA)*, 2016, vol. 111, no. 1, pp. 1–6.
128. Y. Kim, C. Kim, K. Cho, K. Park, and G. Moon, "ZVS Phase Shift Full Bridge Converter with Controlled Leakage Inductance of Transformer," *INTELEC 2009 - 31st International Telecommunications Energy Conference*, pp. 1–5, 2019.
129. J. Dudrik and J. Oetter, "High-Frequency Soft-Switching DC-DC Converters for Voltage and Current DC Power Sources," *Acta Polytechnica Hungarica*, vol. 4, no. 2, pp. 29–46, 2007.
130. K. Park, C. Kim, D. Kim, G. Moon, and M. Youn, "Isolated ZVS Two-Transformer Boost Converter," in *2009 IEEE Energy Conversion Congress and Exposition*, 2009, pp. 693–698.
131. P. K. Sahu, A. Mohanty, B. P. Ganthia, and A. K. Panda, "A Multiphase Interleaved Boost Converter for Grid-Connected PV System," in *2016 International Conference on Microelectronics, Computing and Communications (MicroCom)*, 2016, pp. 1–6.

132. X. Wu, X. Xie, C. Zhao, Z. Qian, and R. Zhao, "Low Voltage and Current Stress ZVZCS Full Bridge DC-DC Converter using Center Tapped Rectifier Reset," *IEEE Transactions on Industrial Electronics*, vol. 55, no. 3, pp. 1470–1477, 2008.
133. M. Ishigaki, J. Shin, and E. M. Dede, "A Novel Soft Switching Bidirectional DC-DC Converter Using Magnetic and Capacitive Hybrid Power Transfer," *IEEE Transactions on Power Electronics*, vol. 32, no. 9, pp. 1–1, 2016.
134. N. O. Sokal and A. D. Sokal, "Class E-A New Class of High-Efficiency Tuned Single-Ended Switching Power Amplifiers," *IEEE Journal of Solid-State Circuits*, vol. 10, no. 3, pp. 168–176, 1975.
135. F. H. Raab, "Idealized Operation of the Class E Tuned Power Amplifier," *IEEE Transactions on Circuits and Systems*, vol. 24, no. 12, pp. 725–735, 1977.
136. M. K. Kazimierczuk and D. Czarkowski, *Resonant Power Converters*, 2nd ed. A John Wiley & Sons, Inc., Publication, 2011.
137. Y. Zhao, W. Li, Y. Deng, and X. He, "Analysis , Design , and Experimentation of an Isolated ZVT Boost Converter With Coupled Inductors," *IEEE Transactions On Power Electronics*, vol. 26, no. 2, pp. 541–550, 2011.
138. C. Wang, C. Lu, C. Lin, and J. Li, "A ZVS-PWM Interleaved Boost DC / DC Converter," in *IEEE International Conference of IEEE Region 10 (TENCON 2013)*, 2013, pp. 1–4.
139. C.-Y. Lin, B.-R., Chiang, H.-K., Tung, C.-Y. and Cheng, "Implementation of an Interleaved ZVS Boost-Type," in *IEEE International Symposium on Industrial Electronics*, 2009, no. ISIE, pp. 819–824.
140. C. Wang, C. Lu, J. Li, and C. Lin, "A ZVS-PWM Interleaved Boost Rectifier," in *2013 1st International Future Energy Electronics Conference (IFEEEC)*, 2013, pp. 48–51.
141. Y. Chen, S. Shiu, and R. Liang, "Analysis and Design of a Zero-Voltage-

- Switching and Zero-Current-Switching Interleaved Boost Converter,” *IEEE Transactions On Power Electronics*, vol. 27, no. 1, pp. 161–173, 2012.
142. B.-R. Lin, “Interleaved Zero-Voltage Switching Three-Level Converter with Less Output Inductor Counts,” *IET Power Electronics*, vol. 10, no. 7, pp. 707–716, 2017.
 143. A. A. Bakar, W. M. Utomo, T. Taufik, and S. Aizam, “DC/DC boost Converter with PI Controller using Real-Time Interface,” *ARNP Journal of Engineering and Applied Sciences*, vol. 10, no. 19, pp. 9078–9082, 2015.
 144. M. Veerachary, S. Member, and M. Pramoda, “Digital PID Compensator Design for Coupled Inductor Boost Converter,” in *2008 Joint International Conference on Power System Technology and IEEE Power India Conference*, 2008.
 145. L. Lv, C. Chang, Z. Zhou, and Y. Yuan, “An FPGA-Based Modified Adaptive PID Controller for DC/DC Buck Converters,” *Journal of Power Electronics*, vol. 15, no. 2, pp. 346–355, 2015.
 146. P. R. Shiyas, S. Kumaravel, and S. Ashok, “Fuzzy Controlled Dual Input DC/DC Converter for Solar-PV/Wind Hybrid Energy System,” *2012 IEEE Students’ Conference on Electrical, Electronics and Computer Science: Innovation for Humanity, SCEECS 2012*, pp. 1–5, 2012.
 147. M. E. Sahin and H. İ. Okumus, “Fuzzy Logic Controlled Buck-Boost DC-DC Converter for Solar Energy-Battery System,” *2011 International Symposium on Innovations in Intelligent Systems and Applications*, vol. 394, no. 6, pp. 394–397, 2011.
 148. N. F. N. Ismail and M. Ieee, “Fuzzy Logic Controller on DC / DC Boost Converter,” in *2010 IEEE International Conference on Power and Energy*, 2010, pp. 661–666.
 149. D. Yang, M. Yang, and X. Ruan, “One-Cycle Control for a Double-Input,” *IEEE Transactions On Power Electronics*, vol. 27, no. 11, pp. 4646–4655, 2012.

150. Y. Xu, Q. Zhang, and K. Deng, "One-Cycle Control Strategy for Dual-Converter Three-Phase PWM Rectifier under Unbalanced Grid Voltage Conditions," *Journal of Power Electronics*, vol. 15, no. 1, pp. 268–277, 2015.
151. K. M. Smedley, "One-Cycle Control of Switching Converters," *IEEE Transactions On Power Electronics*, vol. 10, no. 6, pp. 625–633, 1995.
152. W. Lin, C. Hong, and C. Chen, "Neural-Network-Based MPPT Control of a Stand-Alone Hybrid Power Generation System," vol. 26, no. 12, pp. 3571–3581, 2011.
153. R. Ata, "Artificial neural networks applications in wind energy systems: a review," *Renewable and Sustainable Energy Reviews*, vol. 49, pp. 534–562, 2015.
154. W. M. Utomo, A. Bakar, M. Ahmad, T. Taufik, and R. Heriansyah, "Online Learning Neural Network Control of Buck-Boost Converter," *2011 Eighth International Conference on Information Technology: New Generations*, pp. 485–489, 2011.
155. C. Buccella, C. Cecati, and H. Latafat, "Digital Control of Power Converters — A Survey," *IEEE Transactions On Industrial Informatics*, vol. 8, no. 3, pp. 437–447, 2012.
156. J. L. Calvo-Rolle and E. Corchado, "A Bio-Inspired Knowledge System for Improving Combined Cycle Plant Control Tuning," *Neurocomputing*, vol. 126, pp. 95–105, 2014.
157. V. Mummadi, "Design of Robust Digital PID Controller for H-Bridge Soft-Switching Boost Converter," *IEEE Transactions On Industrial Electronics*, vol. 58, no. 7, pp. 2883–2897, 2011.
158. A. B. Afarulrazi, M. Zarafi, W. M. Utomo, and A. Zar, "FPGA Implementation of Unipolar SPWM for Single Phase Inverter," in *ICCAIE 2010 - 2010 International Conference on Computer Applications and Industrial Electronics*, 2010, no. ICCAIE, pp. 671–676.
159. A. A. Bakar, M. Z. Ahmad, and F. S. Abdullah, "Design of FPGA-Based

- SPWM Single Phase Full-Bridge Inverter,” *International Journal of Integrated Engineering*, vol. 1, no. 3, pp. 81–88, 2009.
160. N. A. Rahim and Z. Islam, “Field Programmable Gate Array-Based Pulse-Width Modulation for Single Phase Active Power Filter,” *American Journal of Applied Sciences*, vol. 6, no. 9, pp. 1742–1747, 2009.
 161. M. Coppola, F. Di Napoli, P. Guerriero, D. Iannuzzi, S. Daliento, and A. Del Pizzo, “An FPGA-Based Advanced Control Strategy of a Grid-Tied PV CHB Inverter,” *Power Electronics, IEEE Transactions on*, vol. 31, no. 1, pp. 806–816, 2016.
 162. C. Buccella, C. Cecati, and H. Latafat, “Digital Control of Power Converters—A Survey,” *IEEE Transactions On Industrial Informatics*, vol. 8, no. 3, pp. 437–447, 2012.
 163. S. Round and R. Duke, “Evaluation of DSP and FPGA Based Digital Controllers for a Single-Phase PWM Inverter,” in *Engineering Conference*, 2004, vol. 1, no. September, pp. 26–29.
 164. “Digital Signal Processing using FPGAs - ppt download.” [Online]. Available: <http://slideplayer.com/slide/4889725/>. [Accessed: 10-Apr-2018].
 165. S. Dusmez, X. Li, and B. Akin, “A New Multi-Input Three-Level Integrated DC/DC Converter for Renewable Energy Systems,” *Conference Proceedings - IEEE Applied Power Electronics Conference and Exposition - APEC*, vol. 2015-May, no. May, pp. 641–646, 2015.
 166. V. Karthikeyan and R. Gupta, “Multiple-Input Configuration of Isolated Bidirectional DC-DC Converter for Power Flow Control in Combinational Battery Storage,” *IEEE Transactions on Industrial Informatics*, vol. 14, no. 1, pp. 2–11, 2018.
 167. Y. Cho and J. S. Lai, “High-Efficiency Multiphase DC-DC Converter for Fuel-Cell-Powered Truck Auxiliary Power Unit,” *IEEE Transactions on Vehicular Technology*, vol. 62, no. 6, pp. 2421–2429, 2013.
 168. M. Moreno, J. Jimenez, J. Villarejo, and E. de Jodar, “Current Sharing in

- Multiphase Zero-Voltage Transition Boost Converter,” *IET Power Electronics*, vol. 5, no. 3, pp. 376–384, Mar. 2012.
169. A. A. Bakar, M. U. Wahyu, A. Ponniran, and T. Taufik, “Simulation and analysis of multiphase boost converter with soft-switching for renewable energy application,” *International Journal of Power Electronics and Drive Systems*, vol. 8, no. 4, 2017.
 170. O. a. Ahmed and J. A. . Bleijs, “An Overview of DC–DC Converter Topologies for Fuel Cell-Ultracapacitor Hybrid Distribution System,” *Renewable and Sustainable Energy Reviews*, vol. 42, pp. 609–626, 2015.
 171. A. B. Afarulrazi, M. U. Wahyu, T. Taufik, S. Aizam, and Jumadri, “Design Study of Zero Voltage Switching for DC/DC Boost Converter,” *Applied Mechanics and Materials*, vol. 785, pp. 136–140, 2015.
 172. M. Sarhangzadeh, S. H. Hosseini, M. B. B. Sharifian, G. B. Gharehpetian, and O. Sarhangzadeh, “Multi-Input Direct DC-AC Converter,” in *CCECE 2011*, 2011, vol. 2, pp. 258–263.
 173. N. Mohan, T. M. Undeland, and W. P. Robbins, *Power Electronics Converters, Applications, and Design*, 3rd ed., vol. 4. John Wiley & Sons, Inc., 2007.
 174. Y. Tao and S. J. Park, “A Novel Ripple-Reduced DC-DC Converter,” *Journal of Power Electronics*, vol. 9, no. 3, pp. 396–402, 2009.
 175. S. Moon, S.-J. Kim, J.-W. Seo, J.-H. Park, C. Park, and C.-S. Chung, “Maximum Power Point Tracking without Current Sensor for Photovoltaic Module Integrated Converter using Zigbee Wireless Network,” *International Journal of Electrical Power & Energy Systems*, vol. 56, pp. 286–297, Mar. 2014.
 176. M. Zarif and M. Monfared, “Step-by-Step Design and Tuning of VOC Control Loops for Grid Connected Rectifiers,” *International Journal of Electrical Power and Energy Systems*, vol. 64, pp. 708–713, 2015.
 177. C. K. Sundarabalan and K. Selvi, “Compensation of voltage disturbances

using PEMFC supported Dynamic Voltage Restorer,” *International Journal of Electrical Power & Energy Systems*, vol. 71, pp. 77–92, 2015.

178. H. Wen and B. Su, “Practical Implementation of an Interleaved Boost Converter for Electric Vehicle Applications,” *Journal of Power Electronics*, vol. 15, no. 4, pp. 1035–1046, 2015.
179. P. F. Miaja, M. Rodríguez, A. Rodríguez, and J. Sebastián, “A Linear Assisted DC/DC Converter for Envelope Tracking and Envelope Elimination and Restoration Applications,” *IEEE Transactions on Power Electronics*, vol. 27, no. 7, pp. 3302–3309, 2012.

